



- FOR YOUR SAFETY**
- WARNING:** Be sure the electricity to the wires you are working on is shut off; either the fuse removed or the circuit breaker off.
- ASSEMBLY**
- NOTE:** Your fixture may be pre-assembled, if so skip steps 1 through 4.
1. With a knife, cut away the flange covering the weep hole.
 2. Pull about 4" of cable into housing through the cable hole.
 3. Using wire connectors, connect cable to wire leads.
 4. Press wire connectors into connector mounts.
- FINAL ASSEMBLY**
5. Attach lead connectors to lamp terminals using terminal screws.
 6. After connections are made, press lamp into groove in housing.

INSTALLATION AND SAFETY INSTRUCTIONS HC-136

INSTALLATION CONTINUED

HC-136

INSTALLATION

1. Dig hole the diameter of plastic pipe and about six inches deeper – fill bottom of hole with gravel for drainage.
2. Attach lead connectors to lamp terminals using terminal screws.
3. Press lamp into groove in housing and insert housing into plastic pipe (if lamp is adjusted to any angle, make sure weep holes are in lowest position).

OUT OF GROUND

Install pipe out of ground with angle face up for vertical to horizontal illumination (adjustable up to 45 degrees).

FLUSH WITH GROUND

Install pipe flush with ground and use 9398 gasket (not included) for vertical illumination (adjustable up to 15 degrees). 9398 gasket snaps into housing.

FINAL INSTALLATION

4. Insert pipe and lamp housing assembly into hole allowing cable to run along surface of ground. Tamp ground to secure in place.
5. Attach fixture cable to main supply cable with 9380 connector.

