

Model:**(91216-147) Neptune 3' lead 12v****(91215-147) Neptune 12v****(91217-147) Neptune 24v****Description: 12V / 24V Solid Brass Area/Path Light****Lamp Provided: 20 Watt AstroBrite Lamps – 20 Watt Max****ASSEMBLY / INSTALLATION INSTRUCTIONS:****Please read carefully before installing. Save these instructions.****Tools Required**

It is recommended that when installing any low voltage fixture that you have (at a minimum) the following items: voltage meter, amp probe, wire nuts, and assorted hand tools

Fixture Assembly Instructions

1. Determine fixture location. Attach the provided stake onto the fixture, until secure. Take care not to twist the wire.
2. Find the point of connection (P.O.C.) location and give yourself a 13-15' lead at P.O.C. Then work from P.O.C. back to the fixture location, route your wire the direction you desire and we recommend that you bury the extra wire near the stake.
3. **Lamping:** Remove the Lens from the Fixture Shroud. Remove the lamp from the box and place it in the socket. **(you can touch the bulbs)** Then install the lens onto the Fixture Shroud and tighten the thumbscrews. Be sure not to over tighten to avoid the possibility of cracking the Lens.


Important safety and maintenance instructions

1. Use with low-voltage outdoor lighting system only.
2. Lamp is hot when lit! Do not touch when lamp is on!
3. Allow fixture to cool before touching or re-lamping fixture!
4. Keep away from materials, structures or landscapes that may burn!
5. Do not operate fixture if cover shield is damaged or missing.
6. Do not submerge fixture in water.
7. Clean fixture with mild soap. Do not use acid or any other solvent base cleaner.

CAUTION: **DO NOT OVERLOAD CABLE or TRANSFORMER** and maintain polarity at all times. For 12 volt systems, keep each fixture between 10.8 and 12 operating volts. For 24 volt systems, keep each fixture between 21.6 and 24.0 operating volts. Consult with a qualified electrical contractor and local electrical codes before installing any electrical product.

UNIQUE LIGHTSCAPING™

a brand of Sea Gull Lighting



- NOTES:
- Lifetime Warranty
 - Maximum Wattage: 20 Watts
 - Included: Frosted & Clear Lens
 - Level of Light Application: 1, 2
 - Weathered Brass Finish

FIXTURE NAME

NEPTUNE

DESCRIPTION

AREA/PATH LIGHT

REV

SCALE: NONE

WEIGHT: 1.8 lbs

8/15/07